

Wireless 2.4GHz DMX 512 Transceiver

anyDMX Wireless™
SIRS-E®



Features

- Reliable wireless DMX 512 signal.
- Up to 400 meters range. (Line of sight)
- A total of 7 frequencies to chose from.
- One unit can both transmit and receive.
- Gender changer included to change from receiver to transmitter.
- Unlimited amount of units can work together.
- Sturdy aluminum construction.
- One year warranty. (From date of purchase)

Product Specs

Model: anyDMX Wireless

Operating Voltage: DC 5V

Max Current: 250mA

Ambient Temperature: -20°C~50°C

Range: 400 m (In line of sight)

IP Rating: IP60 (Non water proof, keep dry at all times)

Working Frequency: 2.4GHz

Dimensions : 209mm x 20mm x 20mm
(8.22in. x .78in. x .78in.)

Set Up Guide and Physical Layout

Quick Set Up Guide

1. Connect power supplies to each unit.
2. Select same color frequency and mode LED light using the frequency changing key on both units. (This is your operating frequency)
3. Connect transmitting unit to DMX console or software. (Gender changer is needed at this point)
4. The frequency and mode LED will begin to flash red on the unit connected as transmitter.
5. At this time, the frequency and mode LED on the receiving unit will flash green. (This means it's receiving)
6. Connect receiving unit to DMX fixture.
7. A successful connection has now been achieved.

Layout

1. DMX output / input
2. DC power input
3. Frequency and mode indicating LED
4. Frequency changing key
5. Antenna

