

Customer Name

Project Name

Part Number

## Product Specs

<b>Model Number:</b>	DMX-TUBE-PROG
<b>Operating Voltage:</b>	12V DC
<b>Control:</b>	DMX512 Protocol
<b>Address Input:</b>	Manual
<b>Data Output:</b>	XLR 3-Pin
<b>Ambient Temperature:</b>	-20°C~60°C
<b>Net Weight:</b>	241.0 g (8.5 oz)
<b>Dimensions:</b>	90 x 65 x 19 mm (3.54 x 2.56 x 0.75 in)
<b>IP Rating:</b>	IP40 (Non water proof, keep dry at all times)

## Setup Instructions

- Starting Address Setup**  
 To set up the starting address, simply use "+" or "-" to change the address. Once you've located the desired address, press "Enter".
- Channel Increments Setup**  
 To change channel increments, hold "Enter" for 3 seconds, press "Enter" again to select "Inc" and use "+" or "-" to change the increment level. Then hold "Enter" for 3 seconds again to save.
- Dimming Levels Setup**  
 To change dimming levels, hold "Enter" for 3 seconds, use "+" or "-" to change Setup Modes and press "Enter" again to select "Lrt", use "+" or "-" again to change the dimming level (dimming levels are 0-255). Then hold "Enter" for 3 seconds again to save.



Vertical Tube DMX Address Writer

## Dimensions and Layout

